

Power-Down Option Addendum

The power down option is completely self contained and detects loss of a primary power failure for longer than approximately 100 ms. The connection to the Silence Sense Sr. is through circuit 2, and is connected to the input by means of a yellow input lead. This feature may be disabled and the circuit 2 input may be used for other sources, such as intrusion detection, etc., by disconnecting the yellow lead from the input connector screw and connecting the desired application.

When applying external power or disconnecting external power to the unit, it is recommended that the back-up battery be disconnected or a false alert will be dialed out. The back-up battery should be replaced every 6 months or at more frequent intervals due to excessive battery drain if there are long periods of power outage encountered.